

# **PRODUCT SPECIFICATION**

# **32** Series Ø22mm Jumbo Dome Pilot Light

"Clear and Easy recognition distance and sides...



## Ø 66mm Large Dome Lens

www.wernerelektrik.com

WERNER

### **32** Series Jumbo Dome Pilot Lights





### **Jumbo Dome Pilot Lights**

#### **Higher Brightness**

The new Jumbo Dome pilot light achieves high brightness.

#### Short Depth behind the Panel

Jumbo Dome type measures only 32mm depth behind the panel.

#### **Panel Mounting**

Pilot lights can be mounted on panels simply by tightening the locking ring.

#### Low Voltage Glow Protective

Pilot lights are protected from glowing at low or leakage voltages. UPTO 5%.

### **O**RDERING TABLE



32 Series WERNER

#### LED lamp Ratings

Туре		6V	12V	24V	110V	230/240 V
Voltage Range	±10%	6V AC/DC	12V AC/DC	24V AC/DC	100/110V AC	230/240V AC
Rated Voltage		6V AC/DC	12V AC/DC	24V AC/DC	110V AC	230/240V AC
Current Draw	AC/DC	16mA (R,A,Y,W) 13mA (G,B)	20mA	20mA	20mA	20mA
Colour		Red				
		Amber				
		Yellow				
		Green				
		Blue				
				White		
Life (reference value)		Approx. 100,000 hours (The luminance is reduced to 50% the initial intensity when used on complete DC.)				
Internal Circuit		(+)		X1 L/// S X2 ///		-K- LED Chip -₩ Protection Diode I Zener Diode


#### Specifications

Operating Temperature	-25 to +60°C (No freezing)		
Storage Temperature	-40 to +80°C		
Operating Humidity	45 to 85% RH (No condensation)		
Insulation Resistance	100 M $\Omega$ minimum (500V DC megger)		
Dielectric Strength	2000VDC For 1 minute		
Vibration Resistance	Operating extremes: 5 to 55 Hz. amplitude 1 mm Damage limits: 30 Hz, amplitude 1.5 mm		
Shock Resistance	Operating extremes: 100 m/s² (15G) Damage limits: 1000 m/s² (100G)		
Degree of Protection	IP40 Front of Panel IP20 Back of Panel		

#### Accessories

Appearance	Part No.	Description
Lens	32.01.03	Jumbo Dome Lens with diffuser Available in specify a lens color code 02-Red, 03-Amber, 04-Yellow, 06-Blue, 09-White
Locking Ring Wrench	45.02.01	Metallic tool used to tighten the plastic locking ring when installing the 32 series control unit in a panel.
Locking Ring	45.95.LR	Tighten the indicator to mounting panel.

#### **Mechanical Specification**



WERNER

32 Series





H.Q. Werner Electric Private Limited

Plot No.: 166, Hebbal Industrial Area, Mysore - 570016, India. Tel: +91 73539 47299, E-mail: info@wernerelektrik.com

#### Werner Malaysia Sdn Bhd,

45-2, Jalan Tiara 2B, Bandar Baru Klang, 41150, Klang, Selangor, Malaysia. Tel: +60 13 533 3348, E-mail: info@wernerelektrik.com

#### Werner Elektrik Türkiye

Ayazağa Mah. Mimar Sinan Sok. Seba Office Boulevard. D Blok. No.: 21D/45 Sariyer / İstanbul, Türkiye. Tekefon: +90 539 829 25 07 , E-posta: info@wernerelektrik.com

www.wernerelektrik.com